OUTDOOR LUMINAIRES — MUSHROOM WALL SCONCE

MUSH-W Mushroom LED Wall Sconce

MUSH-WB · MUSH-WS · 18W | SMD | 2700K / 4000K | Ra80

D180*B110*H230 MM · DIE-CAST AL + PC · 100–240V




KEY FACTS

MUSH-W is a wall-mounted mushroom sconce that fixes where posts cannot go: beside doors, over patio seating and along garden walls. Both families share one 18W SMD engine behind a PC diffuser at 2700K/4000K Ra80 in a D180xB110xH230mm die-cast body.

POWER	18W · WB + WS
SIZE	D180×B110×H230 · 2 models
LIGHT	SMD · 2700K/4000K · Ra80
BODY	AL + PC · 100–240V · Non-dim
FINISH	Light Grey


Entrances · Patios · Garden walls · Courtyards

ORDERING — MUSH-WB WALL SCONCE · 18W



PRODUCT	DIMENSION	CRI	CCT	POWER
371823 18K3/K4	D180*B110*H230mm	Ra80	2700K/4000K	18W

ORDERING — MUSH-WS WALL SCONCE · 18W



PRODUCT	DIMENSION	CRI	CCT	POWER
381823 18K3/K4	D180*B110*H230mm	Ra80	2700K/4000K	18W



APPLICATION

- **Wall or ground → MUSH-W:** open soil beside a walk wants the ground MUSH-D post; a door, patio or garden wall with nowhere to plant a post wants wall-mounted MUSH-W.
- **Mounting rule:** cap centre 60–66 in above the porch floor · 6 in clear of the door frame · hardwired to a standard wall junction box.
- **Count rule:** flank a double door with a pair · single unit on the lock side · 2.5–3 m apart along walls so the pools meet.
- **CCT rule:** 2700K for a warm welcome at entries and garden walls · 4000K where the patio doubles as a task space.

NOTES

- **Ordering suffix:** K3 = 2700K · K4 = 4000K — same CCT choice on both families.
- **Supply & build:** 100–240V direct mains · non-dimmable · die-cast AL + PC in Light Grey.
- **Mounting:** hardwires to a standard wall junction box — a licensed electrician makes the connection, then the D180xB110xH230mm body covers the box.
- **Family guidance:** for ground path rows see MUSH-D · same 18W family, so wall and path lighting read as one scheme.

Scan for live datasheet